

EcoCrankGen for Home or Medium Usage

Model # KSB-3001

Energy Source (Recharging from)	AC Power Adapter
	Cigar Jack in Vehicle
	Hand Crank / Solar Cell / Wind (Optional)
Input Power Requiring for Charging	DC19V / 3A
Hand Crank Generator (Built-In)	None
Rechargeable Battery (Built-In)	12V / 18A
	LiFePo-4
	216 W (Max 1,000 W, Optional)
Output Power (Available Electrical Sources)	DC 12V / 9A : 4 ea
	USB 5V / 500mA : 1 ea
Charging Time, By 2 ways to Charging/Power supply	1 Hour By AC 110~ 230V
	1 Hour By DC from car cigar jack
Operation Hours	LED Light (10W) : 22 hours
	Radio (500mW) : 432 hours
	Portable TV (16W) : 13 hours
	Cellphone (600mA) : 360 hours
ON/OFF	Toggle Switch
Indications	Voltmeter – Digital
	Power Meter – 10 Levels (Red)
Case	Metal / Reinforced Plastic
Color	Yellow
Working Temperature	-40°C ~ 60°C
Relative humidity	80% ~ 90%(40 ± 2°C)
Altitude	≤3000m
Water	Resistant
Shock	Resistant
Safety	Current over-load and over-heating protection
Warranty	24 months
Accessories	AC Adapter
Weight	3.9 Kg
Dimension	200 x 160 x 65 mm



Prepared By
 ANCI Group
www.anci-group.com

It is subject to change without notice for better product